

1(a)(i)	B3A
1(a)(ii)	0001 0000 1000
1(a)(iii)	1 mark for the working 1 mark for the correct denary value Working: Method 1: <pre> 1111 1011 1100 Flip the bits 0000 0100 0011 Add 1 0000 0000 0001 + 0000 0100 0100 </pre> Method 2: -2048 + 1024 + 512 + 256 + 128 + 32 + 16 + 8 + 4 // -128 + 32 + 16 + 8 + 4 Denary value: -68
1(b)(i)	(1) 00101011
1(b)(ii)	1 mark per bullet point, max 2 marks • An overflow error occurs • The answer cannot be represented in the number of bits available // The answer is larger than the maximum positive number that can be stored in the register // The answer is smaller than the most negative number that can be stored in the register

2(a)	3 marks for 6 correct ticks 2 mark for 4 or 5 correct ticks 1 mark for 2 or 3 correct ticks <table><tr><th rowspan="2">Example of data</th><th colspan="7">Number of bits</th></tr><tr><th>4</th><th>8</th><th>16</th><th>24</th><th>32</th><th>64</th><th>128</th></tr><tr><td>the hexadecimal value F139</td><td></td><td></td><td>✓</td><td></td><td></td><td></td><td></td></tr><tr><td>16 000 000 unique amplitude values</td><td></td><td></td><td></td><td>✓</td><td></td><td></td><td></td></tr><tr><td>an IPv4 address</td><td></td><td></td><td></td><td></td><td>✓</td><td></td><td></td></tr><tr><td>256 unique colours</td><td></td><td>✓</td><td></td><td></td><td></td><td></td><td></td></tr><tr><td>an IPv6 address</td><td></td><td></td><td></td><td></td><td></td><td></td><td>✓</td></tr><tr><td>the denary value 65 000</td><td></td><td></td><td>✓</td><td></td><td></td><td></td><td></td></tr></table>	Example of data	Number of bits							4	8	16	24	32	64	128	the hexadecimal value F139			✓					16 000 000 unique amplitude values				✓				an IPv4 address					✓			256 unique colours		✓						an IPv6 address							✓	the denary value 65 000			✓				
Example of data	Number of bits																																																															
	4	8	16	24	32	64	128																																																									
the hexadecimal value F139			✓																																																													
16 000 000 unique amplitude values				✓																																																												
an IPv4 address					✓																																																											
256 unique colours		✓																																																														
an IPv6 address							✓																																																									
the denary value 65 000			✓																																																													
2(b)	1 mark 1111 1001 0100																																																															
2(c)	1 mark 1111 0010																																																															
2(d)	1 mark E33B																																																															

2(a)	1 mark for: 0010 0010 1110 1 mark for: 22E
2(b)(i)	1 mark for: -30
2(b)(ii)	1 mark for smallest, 1 mark for largest Smallest: 1000 0000 Largest: 0111 1111
2(c)	1 mark for application and 1 mark for corresponding justification e.g. • an application that performs financial / banking calculations • because financial transactions use only two decimal places and must be accurate, no accumulating / rounding errors and it is difficult to represent decimal values exactly in normal binary. Or • electronic displays • because visual displays only need to show individual digits • because conversion between denary and BCD is straightforward Or • The storage of the date and time in the BIOS of a PC • because conversion between denary and BCD is more straightforward Or • Barcode systems • because conversion between denary and BCD can be accurately completed

8(a)	1 mark for: Denary value: 8107
------	--

8(b)	1 mark for each bullet point for the method (max 2) e.g. • Flip each bit then add 1 ... • ... method of converting the new binary number into denary • Most significant 1 bit is treated as the corresponding negative denary value ... • ... add the other positive corresponding denary values 1 mark for correct conversion Denary value: -97
8(c)	1 mark each: • A logical shift moves all bits to the right and inserts zeros in the appropriate leftmost bits • An arithmetic shift moves all bits to the right but copies the sign bit into the Most Significant Bit (MSB)

7	1 mark each: • Working – carried values clearly indicated • Correct answer 0001 1000 • Overflow clearly indicated as overflow Example: <pre> 1 0 0 1 1 1 1 0 0 1 1 0 0 0 0 1 + 0 0 0 1 1 0 0 1 ----- (1) 0 0 0 1 1 0 0 0 1 1 1 1 1 1 1(carries) </pre>
---	---

7(a)	1 mark for: 3300 kibibytes
7(b)	1 mark each: • Converting 100 to binary 0110 0100 and 10 to binary 0000 1010 • Subtraction method - converting 10 to – 10 and adding // direct subtraction ... • ... correct answer 0101 1010 Method 1: Converting to -10 and adding: Binary for +10 is 0000 1010 Binary for –10 is 1111 0110 Binary for 100 is 0110 0100 100 + (-10): <pre> 0 1 1 0 0 1 0 0 +1 1 1 1 0 1 1 0 (1) 0 1 0 1 1 0 1 0 Carries: 1 1 0 0 1 0 0 0 </pre> Method 2: Direct Subtraction Borrows: <pre> 0 0 0 1 1 0 1 0 0 1 1 0 0 1 0 0 -0 0 0 0 1 0 1 0 0 1 0 1 1 0 1 0 </pre>
7(c)	1 mark for working: 1100 0000 1111 // 2048 + 1024 + 8 + 4 + 2 + 1 // (12 * 16²) + 15 // (12 * 16 * 16) + 15 // 3072 + 15 1 mark for correct answer: 3087