

6(a)

- **One** mark for working, (all four columns P, Q, R and S)
- **One** mark for first four rows of column Z
- **One** mark for second four rows of column Z

Working space							
A	B	C	P	Q	R	S	Z
0	0	0	1	1	0	0	1
0	0	1	1	1	1	1	1
0	1	0	0	0	1	0	1
0	1	1	0	0	0	0	0
1	0	0	1	0	0	0	1
1	0	1	1	0	1	0	1
1	1	0	0	1	1	0	1
1	1	1	0	1	0	0	0

6(b)(i)

- Two** marks if no errors present
One mark if only one error present

A	BC			
	00	01	11	10
0	0	1	1	0
1	0	1	0	1

6(b)(ii)

- One** mark for each correct loop (**Max 2**)

A	BC			
	00	01	11	10
0	0	1	1	0
1	0	1	0	1

6(b)(iii)

- One** mark for each mark point (**Max 2**)
- One correct Boolean term with a + / OR sign
 - All Boolean terms and operators correct and no other terms present
- $\bar{A}.C + \bar{B}.C + A.B.\bar{C}$

6(a)(i)

- One** mark for each correct loop (**Max 3**)

		AB			
CD		00	01	11	10
00		0	0	0	0
01		1	1	1	0
11		0	1	1	1
10		0	0	1	1

6(a)(ii)

- One** mark per mark point (**Max 2**)

- MP1 One correct Boolean term with an OR sign
 MP2 All three correct Boolean terms connected by OR signs and no other terms present.

$$\bar{A}.\bar{C}.D + B.D + A.C$$

6(b)

- One** mark for correct use of De Morgan's laws
One mark for correct use of any other Boolean algebra law

$$X = A+B+C + \overline{B+C}$$

$$(X=) \bar{A}.\bar{B}.\bar{C} + \bar{\bar{B}.\bar{C}} \dots\dots\dots(\text{De Morgan's})$$

$$(X=) \bar{A}.\bar{B}.\bar{C} + B.\bar{C} \dots\dots\dots(\text{Double negation})$$

$$(X=) \bar{C} . (\bar{A}.\bar{B} + B) \dots\dots\dots(\text{Distributive})$$

One mark for correct answer

$$(X=) \bar{C} . (\bar{A} + B) \dots\dots\dots(\text{Redundancy})$$

6(a)	Three marks for all eight correct products and no additional products Two marks for five, six or seven correct products One mark for three or four correct products $(X =) \bar{A}.\bar{B}.\bar{C}.D + \bar{A}.\bar{B}.C.\bar{D} + \bar{A}.B.\bar{C}.D + \bar{A}.B.C.\bar{D} + A.\bar{B}.\bar{C}.D + A.\bar{B}.C.\bar{D} + A.B.\bar{C}.D + A.B.C.\bar{D}$																									
6(b)	Two marks if no errors present One mark if one error present AB CD ↘ <table border="1"> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> <tr> <th>00</th> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <th>01</th> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> <tr> <th>11</th> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <th>10</th> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> </table>		00	01	11	10	00	0	0	0	0	01	1	1	1	1	11	0	0	0	0	10	1	1	1	1
	00	01	11	10																						
00	0	0	0	0																						
01	1	1	1	1																						
11	0	0	0	0																						
10	1	1	1	1																						
6(c)	One mark for each correct loop (Max 2) AB CD ↘ <table border="1"> <tr> <th></th> <th>00</th> <th>01</th> <th>11</th> <th>10</th> </tr> <tr> <th>00</th> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <th>01</th> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> <tr> <th>11</th> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <th>10</th> <td>1</td> <td>1</td> <td>1</td> <td>1</td> </tr> </table>		00	01	11	10	00	0	0	0	0	01	1	1	1	1	11	0	0	0	0	10	1	1	1	1
	00	01	11	10																						
00	0	0	0	0																						
01	1	1	1	1																						
11	0	0	0	0																						
10	1	1	1	1																						
6(d)	One mark for each mark point (Max 2) MP1 Any correct relevant Boolean term MP2 Boolean terms with correct operator + and no other terms present $(X =) C.\bar{D} + \bar{C}.D // \bar{C}.D. + C.\bar{D}$																									

7(a)	One mark for every two correct products (Max 3) $(T =) \bar{A}.\bar{B}.\bar{C}.D + \bar{A}.\bar{B}.C.D + A.\bar{B}.\bar{C}.D + A.\bar{B}.C.D + A.B.\bar{C}.D + A.B.C.D$
------	--

7(b)	Two marks if no errors present One mark if one error present AB CD ↘ <table><tr><th></th><th>00</th><th>01</th><th>11</th><th>10</th></tr><tr><th>00</th><td>0</td><td>0</td><td>0</td><td>0</td></tr><tr><th>01</th><td>1</td><td>0</td><td>1</td><td>1</td></tr><tr><th>11</th><td>1</td><td>0</td><td>1</td><td>1</td></tr><tr><th>10</th><td>0</td><td>0</td><td>0</td><td>0</td></tr></table>		00	01	11	10	00	0	0	0	0	01	1	0	1	1	11	1	0	1	1	10	0	0	0	0
	00	01	11	10																						
00	0	0	0	0																						
01	1	0	1	1																						
11	1	0	1	1																						
10	0	0	0	0																						
7(c)	One mark for each correct loop (Max 2) AB CD ↘ <table><tr><th></th><th>00</th><th>01</th><th>11</th><th>10</th></tr><tr><th>00</th><td>0</td><td>0</td><td>0</td><td>0</td></tr><tr><th>01</th><td>1</td><td>0</td><td>1</td><td>1</td></tr><tr><th>11</th><td>1</td><td>0</td><td>1</td><td>1</td></tr><tr><th>10</th><td>0</td><td>0</td><td>0</td><td>0</td></tr></table>		00	01	11	10	00	0	0	0	0	01	1	0	1	1	11	1	0	1	1	10	0	0	0	0
	00	01	11	10																						
00	0	0	0	0																						
01	1	0	1	1																						
11	1	0	1	1																						
10	0	0	0	0																						
7(d)(i)	One mark for each mark point (Max 2) - Any correct Boolean term - Boolean terms and operator correct and no other terms present $(T =) A \cdot D + \overline{B} \cdot D // \overline{B} \cdot D + A \cdot D$																									
7(d)(ii)	One mark for simplest form (Max 1) $(T =) D \cdot (A \cdot \overline{B})$																									