1.1 Number systems

Name: _____ Class: _____ Date: _____ **Total: 25 marks**

0 Vocabulary

Word	Example
binary /ˈbaɪnəri/	In **binary**, the number 5 is written 101.
logic gate /ˈlɒdʒɪk geɪt/	An AND gate is a **logic gate**.
processor /ˈprəʊsesə/	The **processor** runs the program's instructions.
register /ˈredʒɪstə/	The processor keeps the number it is using in a **register**.
number system /ˈnʌmbə ˈsɪstəm/	Binary and denary are two kinds of **number system**.
denary /ˈdiːnəri/	We count in **denary**, using the digits 0 to 9.
hexadecimal /ˌheksəˈdesɪml/	In **hexadecimal**, the number 255 is written FF.
base /beɪs/	Binary is **base** 2.
place value /pleɪs ˈvæljuː/	In 352, the **place value** of the 5 is ten.
memory address /ˈmeməri əˈdres/	Each byte in memory has its own **memory address**.
overflow /ˌəʊvəˈfləʊ/	Adding 200 and 100 in one byte causes **overflow**.
logical binary shift /ˈlɒdʒɪkl ˈbaɪnəri ʃɪft/	A **logical binary shift** moves bits left or right and fills the gap with zeros.

exercises.lol exercises.com.cn

Word	Example
→ **least significant bit** /liːst sɪgˈnɪfɪkənt bɪt/	The **least significant bit** is the rightmost bit.
⧓ **two's complement** /tuːz ˈkɒmplɪmənt/	In **two's complement**, 11111111 means −1. 11111111 −1
← **most significant bit** /məʊst sɪgˈnɪfɪkənt bɪt/	The **most significant bit** is the leftmost bit.

1 Key knowledge and worked examples

■ Conversions and two's complement

place value	128	64	32	16	8	4	2	1
bits	**1**	0	0	**1**	0	**1**	**1**	0

$150 = 128 + 16 + 4 + 2 \Rightarrow$ `10010110`

Place values 128…1; the 1s sit under the values that sum to the number

	sign bit (negative)							
place value	−128	64	32	16	8	4	2	1
bits	**1**	**1**	0	**1**	**1**	0	0	0

$-128 + 64 + 16 + 8 = -40$

Two's complement: the MSB is worth −128, so 11011000 = −40

Denary 100 → binary: $64 + 32 + 4 \rightarrow$ `01100100` → hex `64`.

exercises.lol exercises.com.cn

■ **The general methods, step by step**

Denary to binary – divide by 2 and read the remainders bottom-to-top.

step	division	remainder
1	$150 \div 2 = 75$	0
2	$75 \div 2 = 37$	1
3	$37 \div 2 = 18$	1
4	$18 \div 2 = 9$	0
5	$9 \div 2 = 4$	1
6	$4 \div 2 = 2$	0
7	$2 \div 2 = 1$	0
8	$1 \div 2 = 0$	1

Reading bottom-to-top: `10010110`. Check with place values: $128 + 16 + 4 + 2 = 150$.

Binary to hexadecimal – split into nibbles of four bits from the right, then write each as one hex digit: `1100 1010` → `C A` → `CA`. Going back, expand each hex digit into four bits.

Binary addition. Add column by column from the right, carrying 1 when a column makes 2 (`1 + 1 = 10`). If a carry leaves the eighth column, the answer needs a ninth bit that the register cannot hold: that is **overflow** , and the stored answer is wrong.

Logical shift. A left shift of n places moves every bit n to the left, fills the right with zeros and multiplies the value by 2^n; a right shift divides by 2^n. Bits shifted out are lost, so a left shift can also lose the value.

Two's complement. Write the negative number by starting from the positive binary, inverting every bit, then adding 1. To read one, the leftmost bit is worth -128: `11011000` $= -128 + 64 + 16 + 8 = -40$.

Why hexadecimal is used: it is shorter than binary and easier for a person to read and copy without mistakes, and each hex digit maps to exactly four bits. It appears in MAC addresses, IP version 6 addresses, HTML colour codes, memory dumps and error codes.

2 Practice

2.1 Convert the denary number 45 to 8-bit binary. [2]

denary 45 ☐☐☐☐☐☐☐☐

2.2 Convert the binary number `11001010` to hexadecimal. [2]

1 1 0 0 1 0 1 0

2.3 Convert the hexadecimal number `3F` to denary. [2]

hex 3F

2.4 Give two reasons why hexadecimal is used to represent binary numbers, and name two places where it is used. [4]

hexadecimal

3 Exam-style questions

3.1 An 8-bit register can hold the denary values: [1]

☐ **A** 0 to 127
B 0 to 255
C 0 to 256
D 1 to 255

☐☐☐☐☐☐☐☐ 8 bits

exercises.lol exercises.com.cn

3.2 A microprocessor uses 8-bit registers.

(a) Convert the denary number 172 to 8-bit binary. [2]

	1	0	1	1	0	1	0	1
+	0	1	0	1	1	1	0	0

(b) Convert your answer to (a) to hexadecimal. [2]

(c) The register holds `10110101`. This binary number is added to `01011100`. Complete the addition and give the 8-bit answer. [3]

(d) Explain whether overflow has occurred in part (c), and state what overflow means. [2]

(e) The register `00011010` has a logical left shift of 3 places applied. Give the result, and calculate the effect on the denary value. [3]

(f) The same register is used to hold two's complement numbers. Give the denary value of `11101100`. [2]

exercises.lol exercises.com.cn