9.7 Distributed systems fundamentals

Name: _____ Class: _____ Date: _____ **Total: 24 marks**

KEY WORDS Lamport clock • idempotence

Objective

Compute Lamport clocks and design idempotent retries.

1 Key knowledge and worked examples

■ The clock

Send: attach $C + 1$. Receive: $C = \max(C, \text{received}) + 1$ ✓. Course trace: send at 1, receive at 2, send at 3, receive at 4 ✓.

■ Worked example: the one-direction rule

If a happens-before b then $C(a) < C(b)$; the converse is false ✓. A timeout means unknown, not failed ✓.

2 Practice

2.1 P1 at $C = 5$ sends to P0 at $C = 2$. What is P0's next C? [3]

2.2 Can two events share a Lamport value? [3]

2.3 What does idempotence guarantee for a retried operation? [3]

exercises.lol exercises.com.cn

3 Exam-style questions

3.1 P0 (C = 3) and P1 (C = 7) exchange: P0 sends m_1; P1 receives and immediately sends m_2; P0 receives m_2; P0 then sends m_3.

Compute the Lamport value attached to each message and each process's counter after every event (list the sequence). State which pairs are ordered by happens-before and which are concurrent. State why wall clocks could not have produced a guaranteed order. [8]

3.2 A payment service exposes `deduct(user, amount, id)` and clients retry on timeout.

State the double-charge risk and when it fires. Give the idempotent design (key plus ledger) and what the retry returns. State what a timeout proves and what the client should do. Give the rule for choosing which operations must be idempotent. [7]