11.4 Free vibration

Name: _____ Class: _____ Date: _____ **Total: 17 marks**

KEY WORDS natural frequency • damping ratio • underdamped • logarithmic decrement

Objective

Find the natural frequency and static deflection of a machine on its mounts, measure its damping from a decay record, and find the torsional frequency of two discs on a shaft.

1 Key knowledge and worked examples

■ Mass, spring, damper


- $m\ddot{x}+c\dot{x}+kx=0$: **natural frequency** $\omega_n=\sqrt{k/m}$, $f_n=\omega_n/2\pi$, static deflection mg/k.
- **Damping ratio** $\zeta=c/(2\sqrt{km})$; **underdamped** below 1, ringing at $\omega_d=\omega_n\sqrt{1-\zeta^2}$.
- **Logarithmic decrement** $\delta=\ln(x_0/x_1)$ over one period; $\zeta=\delta/\sqrt{4\pi^2+\delta^2}$.
- Two discs on a shaft: $k_t=GJ_p/L$, $J_p=\pi d^4/32$, $\omega=\sqrt{k_t(J_1+J_2)/(J_1J_2)}$.


■ Worked example. The pump on its mounts

$m=120$ kg on four mounts of 75 kN/m, so $k=300$ kN/m.

- $\omega_n=\sqrt{k/m}=\sqrt{300\,000/120}=$ **50.0** rad/s, $f_n=$ **7.96** Hz.
- Peaks 5.0 and 3.1 mm: $\delta=\ln(5.0/3.1)=0.478$, $\zeta=$ **0.076**.
- $c=2\zeta\sqrt{km}=910$ N · s/m; $\omega_d=49.86$ rad/s.

exercises.lol exercises.com.cn





2 Practice

2.1 A 200 kg compressor stands on four mounts of 100 kN/m each. Find ω_n (two decimals, rad/s), f_n (two decimals, Hz) and the static deflection (one decimal, mm). [4]

2.2 A tap test gives successive peaks of 4.0 mm and 2.8 mm one period apart. Find δ (four decimals), ζ (four decimals), c (nearest N · s/m) and ω_d (two decimals, rad/s). [5]

exercises.lol exercises.com.cn

3 Exam-style questions

3.1 A steel shaft ($G = 80$ GPa), 40 mm in diameter and 0.8 m long, joins a flywheel ($J_1 = 1.0$ kg $\cdot$ m^2) to a fan ($J_2 = 0.25$ kg $\cdot$ m^2). (a) Find J_p and k_t (one decimal, kN $\cdot$ m/rad). (b) Find the torsional natural frequency in rad/s, Hz and rpm. (c) Locate the node measured from the flywheel, and say whether running at 1500 rpm is safe. [8]

exercises.lol exercises.com.cn